



'50s Wiring with Four Conductor Wire

KEY:

- Solder Joint
- ≡ Ground Connection (usually soldered to back of volume pot)
- Solder green and white wires together, cover in heat shrink
- Black Wire - Screw Coil Start
- Silver Wire - Shield Ground
- Red Wire - Slug Coil Start
- Green Wire - Screw Coil Finish
- White Wire - Slug Coil Finish

ThroBak Neck Pickup

ThroBak Bridge Pickup

3-Way Toggle Switch

Switch Positions:
1 - Bridge 2 - Bridge & Neck in Parallel 3 - Neck

Bridge Ground Wire

Neck 500K Tone

Neck 500K Vol

.022 μ F Capacitor

Jack Socket

Bridge 500K Vol

.022 μ F Capacitor

Bridge 500K Tone

For normal humbucking wiring, solder green and white wires together, black wire to ground, and the red output wire to the volume pot lugs.

